



ADLINK
TECHNOLOGY INC.

NEON-1020/1040

Quad Core x86 Smart Camera

User's Manual



Manual Rev.: 2.00
Revision Date: May 13, 2015
Part No: 50-1Z168-2000

Advance Technologies; Automate the World.

Revision History

Revision	Release Date	Description of Change(s)
2.00	May 13, 2015	Initial release

Preface

Copyright 2015 ADLINK Technology, Inc.

This document contains proprietary information protected by copyright. All rights are reserved. No part of this manual may be reproduced by any mechanical, electronic, or other means in any form without prior written permission of the manufacturer.

Disclaimer

The information in this document is subject to change without prior notice in order to improve reliability, design, and function and does not represent a commitment on the part of the manufacturer.

In no event will the manufacturer be liable for direct, indirect, special, incidental, or consequential damages arising out of the use or inability to use the product or documentation, even if advised of the possibility of such damages.

Environmental Responsibility

ADLINK is committed to fulfill its social responsibility to global environmental preservation through compliance with the European Union's Restriction of Hazardous Substances (RoHS) directive and Waste Electrical and Electronic Equipment (WEEE) directive. Environmental protection is a top priority for ADLINK. We have enforced measures to ensure that our products, manufacturing processes, components, and raw materials have as little impact on the environment as possible. When products are at their end of life, our customers are encouraged to dispose of them in accordance with the product disposal and/or recovery programs prescribed by their nation or company.

Trademarks

Product names mentioned herein are used for identification purposes only and may be trademarks and/or registered trademarks of their respective companies.

Conventions

Take note of the following conventions used throughout this manual to make sure that users perform certain tasks and instructions properly.



NOTE:

Additional information, aids, and tips that help users perform tasks.



CAUTION:

Information to prevent **minor** physical injury, component damage, data loss, and/or program corruption when trying to complete a task.



WARNING:

Information to prevent **serious** physical injury, component damage, data loss, and/or program corruption when trying to complete a specific task.

Table of Contents

Preface	iii
List of Figures	vii
List of Tables	ix
1 Introduction	1
1.1 Overview	1
1.2 Features	1
1.3 Specifications	2
1.4 Schematics	4
1.5 Indicators	7
1.6 I/O Connectors	8
1.6.1 Digital I/O and Power	9
1.6.2 Ethernet	11
1.6.3 VGA/USB	12
1.7 General Purpose Digital Signals	13
1.7.1 General Purpose Digital Output (EDO)	13
1.7.2 General Purpose Digital Input (EDI)	14
1.7.3 Hardware Trigger Input	14
1.7.4 PWM Light Control Output	14
2 Getting Started	17
2.1 Unpacking Checklist	17
2.2 Connecting a VGA/USB cable	17
2.3 Connecting an Ethernet cable	18
2.4 Connecting a power cable	19
2.5 Operating System Installation	19
2.6 Driver Installation	19
Important Safety Instructions	27

Getting Service 29

List of Figures

Figure 1-1: NEON-1040 Front View.....	4
Figure 1-2: NEON-1020/1040 Rear View.....	5
Figure 1-3: NEON-1020/1040 Side View	6
Figure 1-4: NEON-1020/1040 LED Array.....	7
Figure 1-5: NEON-1020/1040 I/O Array.....	8
Figure 1-6: Digital I/O and Power Connector	9
Figure 1-7: Ethernet Connector.....	11
Figure 1-8: VGA/USB Connector	12
Figure 1-9: General Purpose Digital Output (EDO) Circuit	13
Figure 1-10: General Purpose Digital Input (EDI) Circuit.....	14
Figure 1-11: Hardware Trigger Input Circuit.....	14
Figure 2-1: VGA/USB Alignment Pin (device side)	18
Figure 2-2: Ethernet Alignment Channel (device side)	18
Figure 2-3: Power Alignment Pin (device side).....	19

This page intentionally left blank.

List of Tables

Table 1-1: NEON-1020/1040 LED Function	7
Table 1-2: NEON-1020/1040 I/O Array Legend.....	8
Table 1-3: Digital I/O and Power Pin Assignment.....	10
Table 1-4: Ethernet Pin Assignment.....	11
Table 1-5: VGA/USB Pin Assignment.....	13

This page intentionally left blank.

1 Introduction

1.1 Overview

The NEON-1040 is a powerful new generation x86 smart camera that features the Intel® Atom™ Processor E3845 1.9 GHz, 4 MP at 60 fps, global shutter image sensor, and PWM lighting control support. The NEON-1040 stands out with its minimal footprint and superior computing power, and rugged IP67-rated construction and M12 connectors enable the NEON-1040 to withstand the harshest industrial environments.

High-end quad-core processor with FPGA coprocessors, GPU and up to 32GB storage for image processing, programs, and archiving, all provide advanced image processing ability ideally suited to high speed high resolution industrial imaging. Optimal I/O connectivity includes one additional slave GigE Vision camera connection, 4x digital inputs, 4x digital outputs, and VGA output, all maximizing integration with external devices.

Flexible software development support, including GenTL support for image acquisition and Open CV and Open CL programming, further significantly benefits developers by easing migration from x86 platforms.

1.2 Features

- ▶ Intel® Atom™ Quad-Core Processor E3845 1.91GHz
- ▶ 4MP, 60fps, monochrome global shutter CMOS sensor
- ▶ IP67-rated housing and M12 connectors
- ▶ Advanced image processing support
- ▶ Additional GigE Vision slave camera support
- ▶ Built-in PWM lighting control
- ▶ 4x digital inputs, 4x digital outputs, USB 2.0 port, RS-232 ports
- ▶ VGA output, max. 2048x1152 @60 Hz
- ▶ Flexible software support with STEMMER Common Vision Blox, MVTec HALCON, and many others
- ▶ GeniCam , GenTL, Open CV and Open CL compatible with image acquisition

1.3 Specifications

		NEON-1020	NEON-1040
Processing & Memory			
Processor		Quad core Intel Atom E3845 @ 1.91GHz	
Display		VGA output, max 2048x1152 at 60 Hz.	
RAM		2GB/4GB DDR3L	
Storage		16GB/32GB solid state drive	
Advanced Processing		ROI, LUT, Shading Correction	
Sensor			
Image Sensor		CMV2000	CMV4000
Resolution		2048 x 1088	2048 x 2048
Sensor Size		2/3"	1"
Frame Rate		120fps (8bit) 60fps (12bit)	60fps (8bit) 30fps (12bit)
Format		Monochrome	
Pixel Size (µm)		5.5	
Shutter		Global	
Trigger Mode		External trigger, software trigger, free run	
I/O			
Trigger Input		1x Opto-isolated trigger input	
Digital Output		4x sink type output, max sink 100mA sink voltage max 30VDC	
Digital Input		4x TTL level input	
PWM Lighting Control	Drive Method	Constant current, max. 500 mA	
	Applicable Light Units	12 VDC to 24 VDC illuminators	
Dimming Resolution		1000:1	
Ethernet		1 x GbE	
Serial Communication		1 x RS-232 (TX and RX only)	
USB		1 x USB 2.0	
Physical			
Dimensions		68.5W x 110D x 52.7 mm	
Lens mount		C mount	
Connectors		1xM12 8-pin female, 1xM12 17-pin male, 1x M12 12-pin male	

	NEON-1020	NEON-1040
Software		
OS	Windows 7, Windows Embedded Standard 7	
Environmental & Electrical		
Power Consumption	24 VDC +/-10%, 13W, 0.62A(typical)	
Operating Temperature	0 to 50°C	
Vibration	Operating, 5 Grms, 5-500 Hz, 3 axes	
Certification	IP67, CE, CB, FCC Class A. UL	

1.4 Schematics



- ▶ All units are in millimeters (mm)
- ▶ External dimensions for the NEON-1020 and NEON-1040 are identical




Figure 1-1: NEON-1040 Front View




Figure 1-2: NEON-1020/1040 Rear View




Figure 1-3: NEON-1020/1040 Side View

1.5 Indicators



Figure 1-4: NEON-1020/1040 LED Array

The NEON 1020/1040 provides five labeled LED indicators on the top side, with function as follows.

Indicator	Color	Status	Description
POWER	Blue	On	System power on
		Off	System power off
STATUS	Red	On	Image capture in progress
		Off	Image capture idle
LAN ACT	Green	On	Ethernet port connected and inactive
		Off	Ethernet port disconnected.
		Flashing	Ethernet port connected and active
USER1	Amber	On/Off/ Flashing	User defined LED1
USER2	Green	On/Off/ Flashing	User defined LED2

Table 1-1: NEON-1020/1040 LED Function

1.6 I/O Connectors




Figure 1-5: NEON-1020/1040 I/O Array

A	Power/IO/UART
B	Ethernet
C	VGA/USB

Table 1-2: NEON-1020/1040 I/O Array Legend

1.6.1 Digital I/O and Power




Figure 1-6: Digital I/O and Power Connector

Pin	Signal	Type	Description	17-Pin M12 Pigtail
1	RS232 RXD	Input	RS-232 receive.	Brown
2	DO3/ Strobe out 3	Output	Open-collector output 3 or strobe out 3	Blue
3	DO1/ Strobe out 1	Output	Open-collector output 1 or strobe out 1	White
4	Hardware trigger input (+)	Input	Hardware Trigger input positive	Green
5	Hardware trigger input (-)	Input	Hardware Trigger input negative	Pink
6	PWM light control out (+)	Output	PWM LED control out positive, for connection to LED lighting device; Power source of LED current control is shared System PWR	Yellow

Pin	Signal	Type	Description	17-Pin M12 Pigtail
7	PWM light control out (-)	Output	PWM LED control out negative, for connection to LED lighting device; Power source of LED current control is shared System PWR	Black
8	System PWR	Input	Power input w/ input range +24V +/-10%	Gray
9	System PWR	Input	Power input w/ input range +24V +/-10%	Red
10	RS232 TXD	Output	RS-232 transmit	Violet
11	DO2/ Strobe out 2	Output	Open-collector output 2 or strobe out 2	Gray/Pink
12	DO0/ Strobe out 0	Output	Open-collector output 0 or strobe out 0	Red/Blue
13	DI3	Input	Digital input signal source 3	White/Green
14	DI0	Input	Digital input signal source 0	Brown/Green
15	DI2	Input	Digital input signal source 2	White/Yellow
16	DI1	Input	Digital input signal source 1	Yellow/Brown
17	GND	GND	Ground, reserved for use with ground from power supply	White/Gray

Table 1-3: Digital I/O and Power Pin Assignment



NOTE:

The negative pin of Digital OUT and Digital IN is GND.

1.6.2 Ethernet

M12 8-pin (female) connector that provides communication capabilities at 10 Mbit/sec, 100 Mbit/sec, or 1 Gbit/sec(1000 Mbit/sec).




Figure 1-7: Ethernet Connector

Pin	Signal	Description
1	MDI_3-	Data C-
2	MDI_4+	Data D+
3	MDI_4-	Data D-
4	MDI_1-	Data A-
5	MDI_2+	Data B+
6	MDI_1+	Data A+
7	MDI_3+	Data C+
8	MDI_2-	Data B-

Table 1-4: Ethernet Pin Assignment

1.6.3 VGA/USB

M12 12-pin (male) connector that transmits output video and USB 2.0 signals. The output video signal is a standard RGB analog video output transferring the OS desktop to connected independent display devices. The video output can display an extended Windows and/or an exclusive display.




Figure 1-8: VGA/USB Connector

Pin	Signal	Type	Description
1	USB Power	Output	5 V supplied to USB peripherals
2	USB DATA (+)	Bidirectional	USB data +
3	USB_DATA (-)	Bidirectional	USB data -
4	GND	GND	Ground
5	VGA RED	Output	Red of RGB video signal
6	VGA BLUE	Output	Blue of RGB video signal
7	VGA VSYNC	Output	Vertical sync of RGB video signal

Pin	Signal	Type	Description
8	VGA HSYNC	Output	Horizontal synch of RBG video signal
9	VGA GREEN	Output	Green of RGB video signal
10	GND	GND	Ground
11	VGA DDC SCL	Bidirectional	DDC serial clock line
12	VGA DDC SDA	Bidirectional	DDC serial data line

Table 1-5: VGA/USB Pin Assignment

1.7 General Purpose Digital Signals

1.7.1 General Purpose Digital Output (EDO)

Four digital output channels are provided, such that, in the common ground connection of digital output, as shown, when a 1 (logic high) is written by FPGA to a DO channel, sink current passes through the transistors and the DO channel goes low, and when a 0 (logic low) is written by FPGA to a DO channel, no current passes through the transistors and the DO channel goes high.




Figure 1-9: General Purpose Digital Output (EDO) Circuit

1.7.2 General Purpose Digital Input (EDI)

Four digital input channels are provided.




Figure 1-10: General Purpose Digital Input (EDI) Circuit

1.7.3 Hardware Trigger Input

Four digital input channels are provided.





Figure 1-11: Hardware Trigger Input Circuit

1.7.4 PWM Light Control Output

One channel constant-current sink LED driver, max. constant 500mA output current with 1000 level light control regulates brightness of LED lighting devices, sharing the NEON-1020/1040 System PWR input, requiring that System PWR voltage matches the LED lighting device's operating voltage.



PWM Light Control Output Circuit

This page intentionally left blank.

2 Getting Started

This chapter describes connection and configuration of the NEON-1020/1040.

2.1 Unpacking Checklist

Before unpacking, check the shipping carton for any damage. If the shipping carton and/or contents are damaged, inform your dealer immediately. Retain the shipping carton and packing materials for inspection. Obtain authorization from your dealer before returning any product to ADLINK. Ensure that the following items are included in the package.

- ▶ NEON-1020/1040
- ▶ Quick Start Guide



In environments where temperatures approach 50°C or more, seat the camera face down or in an upright position for optimum heat dissipation efficiency.

Dans les environnements où les températures atteignent les 50°C ou plus, placez la caméra vers le bas ou le haut pour une dissipation thermique optimale.

2.2 Connecting a VGA/USB cable

1. Align the alignment pin (device side) with the alignment channel (cable side)




Figure 2-1: VGA/USB Alignment Pin (device side)

2. Fully insert the cable connector.
3. Tighten the threaded collar (cable side) to fix the connection.

2.3 Connecting an Ethernet cable

1. Align the alignment pin (cable side) with the alignment channel (device side)




Figure 2-2: Ethernet Alignment Channel (device side)

2. Fully insert the cable connector.
3. Tighten the threaded collar (cable side) to fix the connection.

2.4 Connecting a power cable

1. Align the alignment pin (device side) with the alignment channel (cable side)




Figure 2-3: Power Alignment Pin (device side)

2. Fully insert the cable connector.
3. Tighten the threaded collar (cable side) to fix the connection.


2.5 Operating System Installation

The NEON-1020/1040 is compatible with Windows Embedded Standard 7 (WES7E), and supports File-Based Write Filter (FBWF), providing a stable, secure, and high performance software operating environment. The device OS is pre-installed. For other OS support, please contact ADLINK directly.


2.6 Driver Installation


While the following describes NEON-1020/1040 driver installation for WES 7 and Windows 7, with other Windows systems following similar procedures.


1. Run Setup, installation begins.




2. Select Next when prompted until installation is complete.









3. If a Security Warning window appears, select “Install this driver anyway”.



4. If a "Found New Hardware Wizard" window appears, ignore and the window automatically closes after installation is complete.
5. When installation is complete, select Finish.



The device should appear in the Device Manager, as shown



NOTE:

If an error occurs and installation is rolled back, e-mail the file *setupapi.log* in the Windows folder to ADLINK. Log files on Vista systems are moved to %windir%\inf and renamed to *setupapi.app.log* and *setupapi.dev.log* where windir is the Windows folder.

This page intentionally left blank.

Important Safety Instructions

For user safety, please read and follow all **instructions**, **WARNINGS**, **CAUTIONS**, and **NOTES** marked in this manual and on the associated equipment before handling/operating the equipment.

- ▶ Read these safety instructions carefully.
- ▶ Keep this user's manual for future reference.
- ▶ Pay strict attention to all warnings and advisories appearing on the device, to avoid injury or damage.
- ▶ Read the specifications section of this manual for detailed information on the operating environment of this equipment.
- ▶ When installing/mounting or uninstalling/removing equipment:
 - ▷ Turn off power and unplug any power cords/cables.
- ▶ To avoid electrical shock and/or damage to equipment:
 - ▷ Keep equipment away from water or liquid sources;
 - ▷ Keep equipment away from high heat or high humidity;
 - ▷ Keep equipment properly ventilated (do not block or cover ventilation openings);
 - ▷ Make sure to use recommended voltage and power source settings;
 - ▷ Always install and operate equipment near an easily accessible electrical socket-outlet;
 - ▷ Secure the power cord (do not place any object on/over the power cord);
 - ▷ Only install/attach and operate equipment on stable surfaces and/or recommended mountings; and,
 - ▷ If the equipment will not be used for long periods of time, turn off and unplug the equipment from its power source.

- ▶ Never attempt to fix the equipment. Equipment should only be serviced by qualified personnel.

A Lithium-type battery may be provided for uninterrupted, backup or emergency power.



Risk of explosion if battery is replaced with one of an incorrect type. Dispose of used batteries appropriately.

Il y a un risqué d'explosion si la pile est remplacée par une pile de type différent. Eliminez les piles via les points de collecte prévus à cet effet.

- ▶ Equipment must be serviced by authorized technicians when:
 - ▷ The power cord or plug is damaged;
 - ▷ Liquid has penetrated the equipment;
 - ▷ It has been exposed to high humidity/moisture;
 - ▷ It is not functioning or does not function according to the user's manual;
 - ▷ It has been dropped and/or damaged; and/or,
 - ▷ It has an obvious sign of breakage.

Getting Service

Contact us should you require any service or assistance.

ADLINK Technology, Inc.

Address: 9F, No.166 Jian Yi Road, Zhonghe District
New Taipei City 235, Taiwan
新北市中和區建一路 166 號 9 樓
Tel: +886-2-8226-5877
Fax: +886-2-8226-5717
Email: service@adlinktech.com

Ampro ADLINK Technology, Inc.

Address: 5215 Hellyer Avenue, #110
San Jose, CA 95138, USA
Tel: +1-408-360-0200
Toll Free: +1-800-966-5200 (USA only)
Fax: +1-408-360-0222
Email: info@adlinktech.com

ADLINK Technology (China) Co., Ltd.

Address: 上海市浦东新区张江高科技园区芳春路 300 号 (201203)
300 Fang Chun Rd., Zhangjiang Hi-Tech Park
Pudong New Area, Shanghai, 201203 China
Tel: +86-21-5132-8988
Fax: +86-21-5132-3588
Email: market@adlinktech.com

ADLINK Technology Beijing

Address: 北京市海淀区上地东路 1 号盈创动力大厦 E 座 801 室(100085)
Rm. 801, Power Creative E, No. 1 Shang Di East Rd.
Beijing, 100085 China
Tel: +86-10-5885-8666
Fax: +86-10-5885-8626
Email: market@adlinktech.com

ADLINK Technology Shenzhen

Address: 深圳市南山区科技园南区高新南七道 数字技术园
A1 栋 2 楼 C 区 (518057)
2F, C Block, Bldg. A1, Cyber-Tech Zone, Gao Xin Ave. Sec. 7
High-Tech Industrial Park S., Shenzhen, 518054 China
Tel: +86-755-2643-4858
Fax: +86-755-2664-6353
Email: market@adlinktech.com

LiPPERT ADLINK Technology GmbH

Address: Hans-Thoma-Strasse 11, D-68163
Mannheim, Germany
Tel: +49-621-43214-0
Fax: +49-621 43214-30
Email: emea@adlinktech.com

ADLINK Technology, Inc. (French Liaison Office)

Address: 6 allée de Londres, Immeuble Ceylan
91940 Les Ulis, France
Tel: +33 (0) 1 60 12 35 66
Fax: +33 (0) 1 60 12 35 66
Email: france@adlinktech.com

ADLINK Technology Japan Corporation

Address: 〒101-0045 東京都千代田区神田鍛冶町 3-7-4
神田 374 ビル 4F
KANDA374 Bldg. 4F, 3-7-4 Kanda Kajicho,
Chiyoda-ku, Tokyo 101-0045, Japan
Tel: +81-3-4455-3722
Fax: +81-3-5209-6013
Email: japan@adlinktech.com

ADLINK Technology, Inc. (Korean Liaison Office)

Address: 137-881 서울시 서초구 서초대로 326, 802 (서초동, 모인터빌딩)
802, Mointer B/D, 326 Seocho-daero, Seocho-Gu,
Seoul 137-881, Korea
Tel: +82-2-2057-0565
Fax: +82-2-2057-0563
Email: korea@adlinktech.com

ADLINK Technology Singapore Pte. Ltd.

Address: 84 Genting Lane #07-02A, Cityneon Design Centre
Singapore 349584
Tel: +65-6844-2261
Fax: +65-6844-2263
Email: singapore@adlinktech.com

ADLINK Technology Singapore Pte. Ltd. (Indian Liaison Office)

Address: #50-56, First Floor, Spearhead Towers
Margosa Main Road (between 16th/17th Cross)
Malleswaram, Bangalore - 560 055, India
Tel: +91-80-65605817, +91-80-42246107
Fax: +91-80-23464606
Email: india@adlinktech.com

ADLINK Technology, Inc. (Israeli Liaison Office)

Address: 27 Maskit St., Corex Building
PO Box 12777
Herzliya 4673300, Israel
Tel: +972-77-208-0230
Fax: +972-77-208-0230
Email: israel@adlinktech.com

ADLINK Technology, Inc. (UK Liaison Office)

Tel: +44 774 010 59 65
Email: UK@adlinktech.com